

# TG02H



本機は、電源ケーブルの接続に誤りがないことを確認し、電源ケーブルの両端をしっかりと差し込み、電源スイッチをONにします。

- 显示屏分辨率 200dpi
- 显示屏尺寸 57mm
- 显示屏亮度  $> 80$  cd/m<sup>2</sup>
- 显示屏对比度  $\geq 90:1$
- 接口类型 RS232 或 USB (支持 RS232 和 USB 接口)
- 接口数量 1 个
- 接口规格: 符合 RS232 标准, 支持 115200bps 波特率, 8 位数据位, 1 位停止位, 无校验位
- 接口电压 12V 或 24V



??????????????

- ?????????? ?????? ?????- ????? 1D/ 2D (QRCODE)
- ?????????? ?????????????????? ??????: ?????? ?????????????? ?????
- ?????????????????????? ?????????? ?????????? ??????????
- ?????????? ??????????????: ?????????? ?????????????????? -20/+ 70°C
- ?????????? ?????????????????? ? ?????????? ??????????????
- ?????????????? ?????????? ??????????????

????????????

- ?????????????? ??????????????
- ?????????? ??? ?????????????? ??????- ?????
- ?????????????? ??????????????
- ?????????? ?????????????????????????????

????????????


??? ? ?????????:

- ??????????????, ?????????????? ?????????, ?????????? ?????????, ?????? ??? ?????????????? ?????????? ?????????

?????????? ????????

????? ??????	????????????? ? ?????????????? ?????????
?????????? ?????	8 ?????/??
?????????? ?????????? ? ?????	?? ?????????? 24; 32 ? 42 ?????????? ?????????? ? ?????????? ?????
??????????	203 dpi
????????? ?????? (??/ ??)	80 ??/? (????????? 50 ??/?)
??????? ?????????	????????????????? (?? ?????????????), ???????????, ???????????
?????????????????? ??????-????	1D/ 2D QR CODE
?????? ?????????	??????????????, ?????????/????????? ?? 1 ?? 8, ?????????, ??????????????, ??????????????????, ?????????
????????????????? ??????	????????, 180°
????????? ??????	57??
????????????? ??????	?? 55 ?? 60 ??/?
????????? ??????	48 ??
????????? ??????	?? 90??
?????????	?????????????? ?????????, ??????????????? ?????????, ?????? ?????????????????? ?????????, ?????- ?????????
?????????	?????????????? Escape Command
??????????????	RS232 (TTL ??????????), USB, AUX ?????? ??? ?????????? ??????
?????? ??????	8 Kb
?????- ??????	4 Mb
???????? RAM	512 Kb
????????????????? ??????	2 ?????????? 384x682 ?????
?????????	Windows® (32/64 ?????) — ?????????? ?? ?????????? WHQL ? ?????????????????? ?????????????; Linux (32/64 ?????); ????????????????? COM (Linux ??? Windows 32/64 ?????); Android™; iOS
????????? ?????????????????????? ?????? ?????????????????? ?????? ?????????????????? ??????	Pinbase, Pinbase, CustomPowerTool, Custom Windows API
?????????	12 - 24 Vdc ± 10%
C ??????? ?????????????	0.7 A (12Vdc) 0.4 A (24Vdc)
????????? ?????? ?????????????????? ?????????	420 000 ?????? (????????????????? ??????)
????? ??????? ?????????????????? ?????????	50??/100M ?????????????
????????? ?????????????????	-20/+ 70°C
??????????	129(L) x 120(H) x 100(W) ?? (????????? ?????) 126.2(L) x 85.2(H) x 92(W) ?? (????? ? ??????????????)
????	0,33 ?? ??? ?????????????? ??????

???????



915HZ010300300  
PRINTER TG02H USB RS232

Via I. Newton, 4 - 43010 Fontevivo PR - IT02498250345 - +39 0521 680111 - 8RQN7AZ  
04 2026